SIEMENS

Data sheet

6ES7534-7QE00-0AB0



SIMATIC S7-1500 Analog input/output module AI 4x U/I/R/RTD/TC ST; 4 channels in groups of 4; Hardware interrupts; Diagnostics AQ 2x U/I ST; 2 channels in groups of 2; Substitute value; Diagnostics Common mode voltage approx. 10 V 16 bit; Accuracy 0.3%; Delivery including push-in front connector, infeed element, shield bracket and shield terminal

General information	
Product type designation	AI 4xU/I/RTD/TC /AQ 2xU/I ST
HW functional status	From FS01
Firmware version	V1.0.0
FW update possible	Yes
Product function	
• I&M data	Yes; I&M0 to I&M3
 Isochronous mode 	No
Prioritized startup	No
 Measuring range scalable 	No
Scalable measured values	No
 Adjustment of measuring range 	No
Output range scalable	No
Engineering with	
STEP 7 TIA Portal configurable/integrated from version	V13 / V13.0.2
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
 PROFINET from GSD version/GSD revision 	V2.3 / -
Operating mode	
Oversampling	No
• MSI	Yes
• MSO	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	200 mA
Encoder supply	
24 V encoder supply	
Short-circuit protection	Yes
Output current, max.	20 mA; Max. 47 mA per channel for a duration < 10 s
Power	

Power available from the backplane bus	0.7 W
Power loss	
Power loss, typ.	3.3 W
Analog inputs	
Number of analog inputs	4
For current measurement	4
For voltage measurement	4
For resistance/resistance thermometer measurement	2
For thermocouple measurement	4
permissible input voltage for voltage input (destruction limit),	28.8 V
max.	20.0 V
permissible input current for current input (destruction limit),	40 mA
max.	
Constant measurement current for resistance-type transmitter, typ.	150 Ohm, 300 Ohm, 600 Ohm, Pt100, Pt200, Ni100: 1.25 mA; 6 000 Ohm, Pt500, Pt1000, Ni1000, LG-Ni1000: 0.625 mA; PTC: 0.472 mA
Technical unit for temperature measurement adjustable	Yes; °C/°F/K
Analog input with oversampling	No
Standardization of measured values	No
Input ranges (rated values), voltages	
• 0 to +5 V	No
• 0 to +10 V	No
• 1 V to 5 V	Yes
— Input resistance (1 V to 5 V)	100 kΩ
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 ΜΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	100 kΩ
• -2.5 V to +2.5 V	Yes
- Input resistance (-2.5 V to +2.5 V)	10 ΜΩ
• -25 mV to +25 mV	No
• -250 mV to +250 mV	Yes
— Input resistance (-250 mV to +250 mV)	10 ΜΩ
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	100 kΩ
• -50 mV to +50 mV	Yes
— Input resistance (-50 mV to +50 mV)	10 ΜΩ
• -500 mV to +500 mV	Yes
— Input resistance (-500 mV to +500 mV)	10 ΜΩ
• -80 mV to +80 mV	Yes
— Input resistance (-80 mV to +80 mV)	10 ΜΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
- Input resistance (0 to 20 mA)	25 $\Omega;$ Plus approx. 42 ohms for overvoltage protection by PTC
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	25 $\Omega;$ Plus approx. 42 ohms for overvoltage protection by PTC
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	25 $\Omega;$ Plus approx. 42 ohms for overvoltage protection by PTC
Input ranges (rated values), thermocouples	
• Туре В	Yes
— Input resistance (Type B)	10 ΜΩ
• Туре С	No
• Type E	Yes
— Input resistance (Type E)	10 ΜΩ
• Type J	Yes
— Input resistance (type J)	10 ΜΩ
• Туре К	Yes
— Input resistance (Type K)	10 ΜΩ
• Type L	No
• Type N	Yes
— Input resistance (Type N)	10 ΜΩ
• Type R	Yes

— Input resistance (Type R)	10 ΜΩ
	Yes
Type S	10 MΩ
— Input resistance (Type S)	
• Type T	Yes
— Input resistance (Type T)	10 MΩ
• Type U	No
• Type TXK/TXK(L) to GOST	No
Input ranges (rated values), resistance thermometer	Na
• Cu 10	No
• Cu 10 according to GOST	No
• Cu 50	No
 Cu 50 according to GOST Cu 100 	No
	No
 Cu 100 according to GOST Ni 10 	
	No
 Ni 10 according to GOST Ni 100 	No Voc: Standard/alimete
	Yes; Standard/climate
— Input resistance (Ni 100)	10 MΩ No
 Ni 100 according to GOST Ni 1000 	
	Yes; Standard/climate
 Input resistance (Ni 1000) Ni 1000 according to GOST 	No
LG-Ni 1000	Yes; Standard/climate
LG-Ni 1000 — Input resistance (LG-Ni 1000)	res, standard/climate
Input resistance (EG-Ni 1000) Ni 120	No
Ni 120 Ni 120 according to GOST	No
• Ni 200	No
Ni 200 according to GOST	No
• Ni 500	No
Ni 500 according to GOST	No
• Pt 10	No
Pt 10 according to GOST	No
• Pt 50	No
Pt 50 according to GOST	No
• Pt 100	Yes; Standard/climate
— Input resistance (Pt 100)	10 ΜΩ
Pt 100 according to GOST	No
• Pt 1000	Yes; Standard/climate
— Input resistance (Pt 1000)	10 MΩ
Pt 1000 according to GOST	No
• Pt 200	Yes; Standard/climate
— Input resistance (Pt 200)	10 MΩ
Pt 200 according to GOST	No
• Pt 500	Yes; Standard/climate
— Input resistance (Pt 500)	10 MΩ
Pt 500 according to GOST	No
Input ranges (rated values), resistors	
• 0 to 150 ohms	Yes
— Input resistance (0 to 150 ohms)	10 MΩ
• 0 to 300 ohms	Yes
— Input resistance (0 to 300 ohms)	10 MΩ
• 0 to 600 ohms	Yes
- Input resistance (0 to 600 ohms)	10 MΩ
• 0 to 3000 ohms	No
• 0 to 6000 ohms	Yes
- Input resistance (0 to 6000 ohms)	10 MΩ
• PTC	Yes
— Input resistance (PTC)	10 MΩ
Thermocouple (TC)	
Temperature compensation	
— parameterizable	Yes

	Ver
— internal temperature compensation	Yes
— external temperature compensation via RTD	Yes
— Compensation for 0 °C reference point temperature	Yes; fixed value can be set
— Reference channel of the module	No
Cable length	200 m for 1// 200 m for D/DTD_50 m for TC
• shielded, max.	800 m; for U/I, 200 m for R/RTD, 50 m for TC
Analog outputs	
Number of analog outputs	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	24 mA
Current output, no-load voltage, max.	22 V
Cycle time (all channels), min.	3.2 ms; ±0.5 ms, regardless of the number of activated channels
Output ranges, voltage	
• 0 to 10 V	Yes
• 1 V to 5 V	Yes
• -5 V to +5 V	No
• -10 V to +10 V	Yes
Output ranges, current	
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
 for voltage output two-wire connection 	Yes
 for voltage output four-wire connection 	Yes
 for current output two-wire connection 	Yes
Load impedance (in rated range of output)	
 with voltage outputs, min. 	1 kΩ; 0.5 kOhm at 1 to 5 V
 with voltage outputs, capacitive load, max. 	1 µF
 with current outputs, max. 	750 Ω
 with current outputs, inductive load, max. 	10 mH
Cable length	
Cable length	
• shielded, max.	800 m; for current, 200 m for voltage
	800 m; for current, 200 m for voltage
• shielded, max.	800 m; for current, 200 m for voltage
shielded, max. Analog value generation for the inputs	800 m; for current, 200 m for voltage 16 bit
shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel	
shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max.	16 bit
shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable	16 bit Yes
shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms)	16 bit Yes 2,5 / 16,67 / 20 / 100 ms
shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms)	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500,
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500,
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes
 shelded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low Step: Medium 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: Iow Step: High 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: Iow Step: High Analog value generation for the outputs 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low Step: High Analog value generation for the outputs 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low Step: High Analog value generation for the outputs 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values Step: None Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: low Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes Yes Yes Yes Yes Yes
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: Iow Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes Yes <tr< td=""></tr<>
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: None Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes 16 bit 0.5 ms 1.5 ms
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes 16 bit 0.5 ms 1.5 ms 2.5 ms
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: Medium Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for inductive load for inductive load 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes 16 bit 0.5 ms
 shielded, max. Analog value generation for the inputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) additional conversion time for wire-break monitoring additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Time for offset calibration (per module) Smoothing of measured values parameterizable Step: None Step: Medium Step: High Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for inductive load for inductive load 	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 9 / 23 / 27 / 107 ms 9 ms 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms 400 / 60 / 50 / 10 Basic conversion time of the slowest channel Yes 16 bit 0.5 ms 1.5 ms 2.5 ms

 for current measurement as 2-wire transducer 	Yes
— Burden of 2-wire transmitter, max.	820 Ω
 for current measurement as 4-wire transducer 	Yes
 for resistance measurement with two-wire connection 	Yes; Only for PTC
 for resistance measurement with three-wire connection 	Yes; All measuring ranges except PTC; internal compensation of the cable resistances
 for resistance measurement with four-wire connection 	Yes; All measuring ranges except PTC
Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K; With TC type T 0.02 ± % / K
Crosstalk between the inputs, max.	-80 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.02 %
Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-)	0.02 %
Linearity error (relative to output range), (+/-)	0.15 %
Temperature error (relative to output range), (+/-)	0.002 %/K
Crosstalk between the outputs, max.	-100 dB
Repeat accuracy in steady state at 25 °C (relative to output range), (+/-)	0.05 %
Temperature error of internal compensation	±6 °C
note regarding accuracy	at temperatures below 0 °C, the figures for operating error and temperature error are doubled
Operational error limit in overall temperature range	
Voltage, relative to input range, (+/-)	0.3 %
• Current, relative to input range, (+/-)	0.3 %
• Resistance, relative to input range, (+/-)	0.3 %
• Resistance thermometer, relative to input range, (+/-)	0.3 %; Ptxxx standard: ±1.5 K, Ptxxx climate: ±0.5 K, Nixxx standard: ±0.5 K, Nixxx climate: ±0.3 K
• Thermocouple, relative to input range, (+/-)	0.3 %; Type B: > 600 °C ±4.6 K, type E: > -200 °C ±1.5 K, type J: > -210 °C ±1.9 K, type K: > -200 °C ±2.4 K, type N: > -200 °C ±2.9 K, type R: > 0 °C ±4.7 K, type S: > 0 °C ±4.6 K, type T: > -200 °C ±2.4 K
Voltage, relative to output range, (+/-)	0.3 %
• Current, relative to output range, (+/-)	0.3 %
Basic error limit (operational limit at 25 °C)	
 Voltage, relative to input range, (+/-) 	0.1 %
 Current, relative to input range, (+/-) 	0.1 %
 Resistance, relative to input range, (+/-) 	0.1 %
• Resistance thermometer, relative to input range, (+/-)	0.1 %; Ptxxx standard: ±0.7 K, Ptxxx climate: ±0.2 K, Nixxx standard: ±0.3 K, Nixxx climate: ±0.15 K
• Thermocouple, relative to input range, (+/-)	0.1 %; Type B: > 600 °C ±1.7 K, type E: > -200 °C ±0.7 K, type J: > -210 °C ±0.8 K, type K: > -200 °C ±1.2 K, type N: > -200 °C ±1.2 K, type R: > 0 °C ±1.9 K, type S: > 0 °C ±1.9 K, type T: > -200 °C ±0.8 K
 Voltage, relative to output range, (+/-) 	0.2 %
• Current, relative to output range, (+/-)	0.2 %
Interference voltage suppression for $f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f1 = interference voltage suppression for f = n x (f1 + /-1 \%), f$	erence frequency
 Series mode interference (peak value of interference < rated value of input range), min. 	40 dB
Common mode voltage, max.	10 V
Common mode interference, min.	60 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Substitute values connectable	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	Yes; two upper and two lower limit values in each case
Diagnoses	
6	Yes
Monitoring the supply voltageWire-break	Yes Yes; only for input type 1 5 V, 4 20 mA, TC, R, RTD and output type current
Short-circuit	Yes; Only for output type "voltage"
Overflow/underflow	Yes
Diagnostics indication LED	
• RUN LED	Yes; green LED

last modified:	10/9/2024 🖸
	for integration time = 2.5 ms: Voltage: $\pm 250 \text{ mV} (\pm 0.02\%)$, $\pm 80 \text{ mV} (\pm 0.05\%)$, $\pm 50 \text{ mV} (\pm 0.05\%)$; resistance: 150 Ohms ($\pm 0.02\%$); resistance thermometer: Pt100 climate: $\pm 0.08 \text{ K}$, Ni100 climate: $\pm 0.08 \text{ K}$; thermoelement: Type B, R, S: $\pm 3 \text{ K}$, type E, J, K, N, T: $\pm 1 \text{ K}$
Note:	Supplied incl. 40-pole push-in front connectors. Additional basic error and noise
Weight, approx. Other	250 g
Weights	250 ~
Depth	129 mm
Height	147 mm
Width	25 mm
Dimensions	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Altitude during operation relating to sea level	
 vertical installation, max. 	40 °C
 vertical installation, min. 	-25 °C; from FS04
 horizontal installation, max. 	60 °C
 horizontal installation, min. 	-25 °C; from FS04
Ambient temperature during operation	
Ambient conditions	
data integrity	No
signed firmware update	No
product functions / security / header	
 — global warming potential, (after end of life cycle) [CO2 eq] 	-0.44 kg
 global warming potential, (during operation) [CO2 eq] 	24.6 kg
 — global warming potential, (during production) [CO2 eq] 	14.4 kg
— global warming potential, (total) [CO2 eq]	38.6 kg
Global warming potential	20.6 kg
environmental product declaration	Yes
Ecological footprint	Voc
Standards, approvals, certificates	
	707 V DC (type test)
Isolation tested with	707 V DC (type test)
solation	8 V DC
Between the inputs and MANA (UCM) between S- and MANA (UCM)	10 V DC 8 V DC
between the inputs (UCM)	20 V DC
Permissible potential difference	
Between the channels and load voltage L+	Yes
 between the channels, in groups of between the channels and backplane bus 	2 Yes
between the channels	No
Potential separation analog outputs	Na
Between the channels and load voltage L+	Yes
between the channels and backplane bus	Yes
between the channels, in groups of	4
between the channels	No
Potential separation analog inputs	Na
Potential separation	
for module diagnostics	Yes; red LED
 for channel diagnostics 	Yes; red LED
Channel status display	Yes; green LED
 Monitoring of the supply voltage (PWR-LED) 	Yes; green LED